

IN THE CLAIMS

Please enter the following indicated amendments.

1. (Withdrawn) A delay circuit comprising

- a first network having an input and an output node;
- a second network having an input and an output,
 - the input of the second network being coupled to the output node of the first network;

the first network and the second network being configured such that:

- a glitch at the input to the first network having a length of approximately one-half of a standard glitch time or less does not cause the voltage at the output of the second network to cross a threshold;
- a glitch at the input to the first network having a length of between approximately one-half and two standard glitch times causes the voltage at the output of the second network to cross the threshold for less than the length of the glitch; and
- a glitch at the input to the first network having a length of greater than approximately two standard glitch times causes the voltage at the output of the second network to cross the threshold for approximately the time of the glitch.

2. (Withdrawn) The delay circuit of claim 1 wherein

- the first network comprises a P-type FET and an N-type FET, the gates of the two FETs being coupled together and the drains of the two FETs being coupled together, the source of the P-type FET being coupled to the power source and the source of the N-type FET being coupled to ground.

3. (Withdrawn) The delay circuit of claim 2 wherein the channel of at least one of the FETs is non-linear.
4. (Withdrawn) The delay circuit of claim 3 wherein the channel of the at least one of the FETs includes a jog.
5. (Withdrawn) The delay circuit of claim 1 wherein the jog is a right angle.
6. (Withdrawn) The delay circuit of claim 1 wherein the second network is an inverter.
7. (Withdrawn) The delay circuit of claim 1 wherein the voltage at the output of the second network crosses the threshold after a delay relative to the arrival of the glitch at the input to the first network, the delay being determined by characteristics of the first network and characteristics of the second network.
8. (Currently Amended) An SEU-resistant circuit comprising
 - a logic gate having an input and an output;
 - a feedback path from the output of the logic gate to the input of the logic gate, the feedback path comprising two or more [delay] logic elements, said logic gate and said two or more logic elements each comprising an input to output pulse response operable for delaying a propagation time of a pulse propagating therethrough and for selectively reducing a pulse width thereof; and
 - the logic gate and the two or more [delay] logic elements being [configured to absorb a standard] operable for reducing in size an instance of a potentially SEU producing glitch introduced at the input [to] of the logic gate before [it] the potentially SEU producing glitch propagates through

the feedback path to the input of the logic gate, the input to output pulse response of the logic gate and the two or more logic elements being substantially similar in that the resulting amount of pulse propagation delay and amount of reduction of the pulse width of the potentially SEU producing glitch [being] is spread substantially evenly among the logic gate and the two or more [delay] logic elements.

9. (Cancelled).

10. (Currently Amended) The SEU-resistant circuit of claim 8 wherein [the delay elements comprise balanced gates] the input to output pulse response of the logic elements is balanced such that a rise time and fall time of the input to output pulse response is approximately the same for each of the logic elements.

11. (Currently Amended) The SEU-resistant circuit of claim 8 [wherein the feedback path further comprises a driver gate] further comprising a plurality of logic gates, an input to output pulse response of the plurality of logic gates and the two or more logic elements being configured to produce a pulse propagation delay approximately no longer than a maximum pulse propagation delay of the slowest of the plurality of logic gates when the slowest logic gate is fully loaded with maximum fan out.

12. (Currently Amended) The SEU-resistant circuit of claim [8] 11 wherein [the delay elements comprise inverters] the input to output pulse response of the plurality of logic gates and each of the two or more logic elements is operable to prevent a glitch with a time length less than approximately one-half of the maximum pulse propagation delay from passing through the plurality of logic gates or through each of the two or more logic elements

without being reduced in size such that said glitch is unable to trigger a subsequent logic element.

13. (Currently Amended) The SEU-resistant circuit of claim [8] 11 wherein [the number of delay elements is even] the input to output pulse response of the plurality of logic gates and the two or more logic elements does not substantially reduce the time length of a pulse with a time length greater than two times the maximum pulse propagation delay.
14. (Withdrawn) An SEU-resistant circuit having a first state and a second state, the SEU-resistant circuit comprising
- a first flip-flop having a first state and a second state, the first flip-flop configured to change state upon application of a signal to a first flip-flop signal input;
 - a second flip-flop having a first state and a second state equivalent to the first state and the second state of the first flip-flop, the second flip-flop configured to change state upon application of a signal to a second flip-flop signal input;
 - the first flip-flop being coupled to the second flip-flop such that the SEU-resistant circuit does not change from its first state to its second state unless the state of the first flip-flop agrees with the state of the second flip-flop;
 - an input to receive a signal to cause the SEU-resistant circuit to change states when the signal changes states;
 - the input coupled to the first flip-flop signal input;
 - the input coupled to the second flip-flop signal input through a delay circuit; and
 - the input is for one of a clock, reset or preset signal.
15. (Withdrawn) The SEU-resistant circuit of claim 14, wherein
- the delay circuit is non-inverting.

16. (Withdrawn) The SEU-resistant circuit of claim 14, wherein
the delay circuit has a delay greater than the maximum expected glitch time.
17. (Withdrawn) A transition NAND gate comprising
two or more input nodes;
an output node;
a state machine responsive to the two or more input nodes;
the state machine being in a current state when signals applied to the respective input
nodes have specified values;
the state machine being capable of transitioning from a most recent current state to a state
that is not a current state;
the output node storing the current state of the state machine.
18. (Withdrawn) The transition NAND gate of claim 17 wherein
the output node has parasitic capacitance and the output node stores the current state in its
parasitic capacitance.

19. (Withdrawn) The transition NAND gate of claim 17 wherein the state machine comprises:

a supply-side FET for each input terminal,

the gate of each supply-side FET being connected to a respective input terminal,

the supply-side FETs being connected in series,

the series-connected supply-side FETs having a supply end and an output end;

a ground-side FET for each input terminal,

the gate of each ground-side FET being connected to a respective input terminal,

the ground-side FETs being connected in series,

the series-connected ground-side FETs having a ground end and an output end;

the output end of the series-connected supply-side FETs being connected to the

output end of the series connected ground-side FETs to form an output terminal.

20. (Withdrawn) The transition NAND gate of claim 19 wherein

the supply-side FETs are P-type FETs; and

the ground-side FETs are N-type FETs.

21. (Withdrawn) The transition NAND gate of claim 17 wherein

the state machine is in a first current state when signals connected to the input nodes are all high; and

the state machine is in a second current state when signals connected to the input nodes are all low.

22. (Withdrawn) An SEU-resistant flip-flop comprising

- a Data input;
- a GB input;
- a network responsive to signals applied to the Data input and the GB input;
- the network having a Q1 output which has the value of the signal applied to the Data input when the signal applied to the GB input is low;
- the network having a Q2 output which has the value of the signal applied to the Data input D seconds after the signal applied to the GB input is low;
- the Q1 output of the network being coupled to a Q1 node;
- the Q2 output of the network being coupled to a Q2 node;
- a two-input one-output TAG, the output of the TAG being configured to change state only if the value of the signal on its first input is the same as the value of the signal on its second input;
- the first input of the TAG being coupled to the Q1 node;
- the second input of the TAG being coupled to the Q2 node;
- the output of the TAG being coupled to a QB node;
- a first slow inverter having its input coupled to the QB node and its output coupled to the Q1 node; and
- a second slow inverter having its input coupled to the QB node and its output coupled to the Q2 node.

23. (Withdrawn) The SEU-resistant flip-flop of claim 22 further comprising

- a transmission gate, gated by the value of the signal in the GB node, in a signal path between the first slow inverter and the Q1 node; and
- a transmission gate, gated by the value of the signal on the GB node, in a signal path between the second slow inverter and the Q2 node.

24. (Withdrawn) The SEU-resistant flip-flop of claim 22 further comprising

- an inverter coupled to the QB node.

25. (Withdrawn) The SEU-resistant flip-flop of claim 22 wherein the TAG comprises
- two series-connected P-type FETs, the gate of a first P-type FET coupled to the Q1 node, the gate of a second P-type FET coupled to the Q2 node, the series-connected P-type FETs having a supply end and a connection end;
 - two series-connected N-type FETs, the gate of a first N-type FET coupled to the Q1 node, the gate of a second N-type FET coupled to the Q2 node, the series-connected N-type FETs having a ground end and a connection end; and
 - the connection end of the series-connected N-type FETs being coupled to the connection end of the series-connected P-type FETs and to the QB node.
26. (Withdrawn) The SEU-resistant flip-flop of claim 25 wherein
- the P-type FET coupled to the Q2 node is at the connection end of the series-connected P-type FETs; and
 - the N-type FET coupled to the Q2 node is at the connection end of the series-connected N-type FETs.
27. (Withdrawn) The SEU-resistant flip-flop of claim 22 wherein the network comprises
- a first inverter having its input coupled to the GB input, the output of the first inverter being coupled to a G node;
 - a delay G having its input coupled to the G node, the output of the delay G being coupled to a G2 node;
 - an inverter having its input coupled to the G2 node and its output coupled to a GB2 node;
 - a first transmission gate coupled between the Data input and the Q1 node and gated by the signals on the GB and G nodes; and
 - a second transmission gate coupled between the Data input and the Q2 node and gated by the signals on the GB2 and G2 nodes.
28. (Withdrawn) The SEU-resistant flip-flop of claim 27 wherein the delay G comprises
- a first delay coupled in series with a second delay.

29. (Withdrawn) The SEU-resistant flip-flop of claim 27 further comprising
a buffer coupled between the Data input and the first and second
transmission gates.
30. (Currently Amended) A method for reducing the vulnerability of an [latch] electronic circuit
to single event upsets, comprising: [the latch comprising a gate having an input and an
output and a feedback
path from the output to the input of the gate, the method comprising]
providing one or more logic gates for said circuit with a feedback path from an output of
a respective of the one or more logic gates to an input thereof;
inserting [a delay] one or more logic elements into the feedback path; and
providing [a delay in the] that the one or more logic circuits and the one or more
logic gates each have an input to output pulse response such that an initial input
glitch with a pulse width less than a pulse width L1 effectively does not pass
through a respective of the one or more logic circuits or a respective of the one or
more logic gates because a resulting diminished output glitch is not capable of
triggering a change of state of a subsequent logic element; and
providing that if the initial input glitch has a pulse width greater than pulse width
L1 but less than a pulse width L2 then the resulting diminished output glitch
effectively passes through the respective of the one or more logic circuits or the
respective of the one or more logic gates because the resulting output glitch is
then capable of triggering a change of state of the subsequent logic device but that
the resulting diminished output glitch then has a reduced pulse width as compared
to the initial input glitch; and
providing that the pulse width L1 and the pulse width L2 are approximately equal
for the respective of the one or more logic circuits and for the respective of the
one or more logic gates.

31. (Currently Amended) The method of claim 30 wherein the one or more logic gates comprise[s] a first FET [having] comprising a first channel and a second FET [having] comprising a second channel, [the channel of the first FET and the channel of the second FET coupled at a node having a parasitic capacitance], wherein said providing step comprises:
- adjusting the characteristics of the first channel of the first FET[, the characteristics of the channel of the second FET and the parasitic capacitance of the node].
32. (Currently Amended) The method of claim 31 wherein said step of adjusting comprises [increasing] changing at least one of a width or [the] a length of the first channel of the first FET.
33. (Currently Amended) The method of claim 32 wherein [increasing] said step of changing comprises making the first channel [non-linear] wider.
34. (Currently Amended) The method of claim [33] 31 wherein said step of adjusting [making] comprises inserting a [jog] non-linearity into the first channel.
35. (Currently Amended) The method of claim 34 wherein the [jog] non-linearity is a right angle.
36. (Currently Amended) The method of claim 31 [further comprising:] wherein an input signal pulse having a signal pulse width greater than a pulse width L3 effectively passes through the respective one or more logic gates or passes through the respective one or more logic circuits without a substantial change in a resulting output signal pulse width.
- [coupling the output of the gate to a threshold device having an input, an output and a threshold, the output having a first value when the input is less than the threshold and a second value when the input is greater than the threshold.]

37. (Currently Amended) The method of claim 31 further comprising:

providing that said one or more logic gates and the one or more logic circuits comprises a latch circuit.

[adjusting the time constant and the threshold so that

a glitch of length $L1$ at the input to the gate would not effect the output of the threshold device;

a glitch of length $L2$, $L1 < L2 < L3$, would cause a pulse of length $L4 < L2$ to appear at the output of the threshold device after a delay determined by the time constant and the threshold; and

a glitch of length $L5 > L3$ would cause a pulse of length approximately $L5$ to appear at the output of the threshold device after a delay determined by the time constant and the threshold.]